



## Multi-Plus Lighting Setup

Easy to follow instructions for:

### Hayward OmniLogic®

(Note: ProLogic® controls do NOT support Multi-Plus integration)

---

(Use your watch or phone to count the seconds accurately)

- Step 1:** Set controller to **Universal ColorLogic®**.
- Step 2:** Place panel in **Service Mode > HVR menu**. (use panel for switching lights on and off)
- Step 3:** Make sure lights have been off for **1 minute**.
- Step 4:** Turn lights **on for 2 seconds**, then **off for 12 seconds**.
- Step 5:** Repeat - Turn lights **on for 2 seconds**, then **off for 12 seconds**.
- Step 6:** Repeat again- Turn lights **on for 2 seconds**, then **off for 12 seconds**.
- Step 7:** **Turn on lights** - will be flashing RED. (if not, repeat steps 2 through 7).
- Step 8:** Turn off and on until lights are **flashing YELLOW**.
- Step 9:** **Turn off lights for at least one minute**.

Your setup should now be complete. To confirm the system is working correctly, select a color via the controller or wall switch (depending on operating mode selected) and check to ensure all lights are synchronized and the correct color is displayed.

visit [www.1paramount.com/paraglo-mp-setup/](http://www.1paramount.com/paraglo-mp-setup/) for additional video instructions

REV 011618